

# SPORTident

## SPORTident BSF6 control stations, sw version 4.06 / 4.07

- Functions: clear, check, start, control and finish.
- Code numbers in control function: 31-255
- Code numbers for other function : 1-30
- Equipped with a real time clock (RTC). When enabled the clock is always running in 12h format, even in training mode.
- Feedback with light and sound, can be disabled.
- Internal backup memory, 4032 punches.
- Programmable via inductive coupling (no cables)
- Powered by alkaline battery pack (3\*AA),
- 400 hours in active mode
- Size: 113\*62\*31 mm mm<sup>3</sup>
- weight 202 gram incl battery pack
- A yellow blinking status LED is visible from the bottom side of the control station and



### Quick command sticks („lilac cards“)

- Turn-off
- Clear backup memory

Both command sticks are working only in conjunction with the activated „training mode“ feature of the control station.

### Compatibility

- The control stations are optimized to communicate with main stations having software version 3.01 and higher.
- Software 4.x does not work together with master stations having lower software versions than 2.33.
- In all applications SPORTident control stations used in „clear“ and „check mode“ must have the same software version.

### SIMAN9.8

The BSF6 control station has to be programmed by inductive coupling using the main station connected to the PC and a coupling stick. To use all the features **SIMAN9.8** should be used. It is not allowed to work with SIMAN9.5x and lower. The programming mechanism is described in the help-text of the SIMAN.

Please read the SIMAN help description first !!

To achieve a good coupling between the master station and the control station to be programmed the control station has to be placed upside-down. Both stations should be connected using the coupling stick.

Turning off the station by disconnecting the battery-plug has the consequence that the power consumption for the present session can not be stored. The power-meter will go wrong.

**Known errors:** There are no errors known.

### Hard- and Software updates

No more updates will be available for this station.

**Good luck with SPORTident !**